

موتور برق



D-NIRO

دیزل نیرو

واردات و فروش انواع موتور برق های خانگی و صنعتی

Specifications:

6500 W RGX6500E

[> View Spec Sheet](#)

Type	Brush Type
Voltage Regulation	AVR
Frequency	60 HZ
Voltage	120/240
Phase	Single
Max. Output (watts)	6500
Max. Amps	54.2/27.1
Rated Output (watts)	5000
Rated Amps	41.7/20.8
dbA Rating @ rated output (7 meters)	75
Current Protection	GFCI and Fuseless Circuit Breaker
Engine Model	EX35 - 12 HP
Engine Type	Subaru OHC
Low Oil System	Shutdown
Fuel	Gasoline
Fuel Tank Capacity	7.3 gallons
Continuous Operation (hours at rated load)	8.3 hours
Starting System	Electric with Recoil backup
Battery Recommendation (or equal)	Interstate SP40
Dimensions (L x W x H)	35" x 22" x 24"
Dry Weight lbs	207
Receptacle	120V. 20A. GFCI Duplex (2)
Receptacle	120V. 30A. Twistlock (1)
Receptacle	120/240V. 30A. Twistlock (1)
12V DC Charging	Standard
Hourmeter	Standard
Pilot Lamp	Standard
Idle Control	Standard
Full Power Switch	Standard
Wheel Kit	Optional
Tier III California Compliant	Yes



Select an image.



[> See larger image and other views.](#)

Top Stories:

[Emissions Education](#)

[Time for a Tune-Up](#)

[Pam Meyer Elected to ARA Board of Directors](#)