



# دیزل نیرو

واردات و فروش انواع دیزل ژنراتورهای صنعتی

- **Possibilità di alimentare qualsiasi tipo di carico**  
Possibility to supply any type of load  
Posibilidad de alimentar cualquier tipo de carga
- **Compatto e facile da assemblare**  
Compact and easy to assemble  
Compacto y fácil de montar
- **Alta capacità di avviamento**  
High starting capacity  
Alta capacidad de arranque
- **Alto rendimento**  
High efficiency  
Alto rendimiento

**Alternatori sincroni trifase con spazzole con regolazione mista - 2 poli**  
Three-phase synchronous alternators with brushes and mixed regulation - 2 poles  
Alternadores síncronos trifásicos con escobillas y regulación mixta - 2 polos

## > E1S KE



La serie E1S KE è costituita da alternatori trifase a 2 poli con spazzole e regolazione mista compound ed elettronica (AVR).

E1S KE series are three-phase 2 poles alternators with brushes and mixed compound and electronic regulation (AVR).

La serie E1S KE está constituida por alternadores trifásicos de 2 polos con escobillas y regulación mixta compound y electrónica (AVR).

Tipo Type	50 Hz - 3000 rpm - $\cos\phi = 0.8$					60 Hz - 3600 rpm - $\cos\phi = 0.8$				
	Pot. resa Rating Pot. salida kVA	Rendimento% Efficiency % Rendimiento %		Pot. assorbita Driving power Pot. entrata kW    HP		Pot. resa Rating Pot. salida kVA	Rendimento% Efficiency % Rendimiento%		Pot. assorbita Driving power Pot. entrata kW    HP	
		4/4	3/4	kW	HP		4/4	3/4	kW	HP
E1S10M G KE	4.5	78.5	79.0	4.6	6.2	5.4	79.0	80.0	5.6	7.6
E1S10M H KE	5.5	80.5	81.0	5.4	7.2	7	81.0	82.0	6.9	9.4
E1S10M I KE	7	82.5	83.0	6.7	9.0	8.5	82.5	83.0	8.3	11.3
E1S10L L KE	9	82.7	83.1	8.7	11.7	11	82.8	83.4	10.6	14.2
E1S11M AS KE	10	83.0	83.2	9.6	12.2	12.5	83.5	83.7	11.5	15.6
E1S11M B KE	11.5	83.5	83.7	11.0	14.8	14	84.0	84.3	13.4	18.3